

PAD-250/500



Professional Series – Mixer Amplifier with built in Bluetooth and USB/SD Card

The PAD-250/500 Mixer Amplifier with USB and BT. The PAD-250/500 mixer amplifier is a professional tool with a sleek industrial look, designed and built for demanding commercial sound applications. The latest technology is built in, which significantly reduces size and weight, and all amps are highly efficient, with Colling fan, and simple to install and operate.

Key Features:-

- * Output power is 250W/500W
- * Frequency Response: Mic: (200Hz - 18KHz) Line : 100Hz - 19KHz)
- * TDH @ 1KHz less than 1%
- * Input Sensitivity : Mic Input: -40dB (10mV) Line: -8dB(400mV)
- * Input Interface : Mic 1:6 35mm, Mic 2/Line 3: XLR/6.35mm.Line 1& 2 RCA.
- * Output Interface : 4-16Ohms, 70V, 100V, 6-Zones 100V
- * Signal to Noise Ratio : Mic: >80dB, Line: > 85dB
- * Power Supply: 110/220V AC
- * Dimensions WxHxD: 484x89x340mm
- * Rack PA amplifier



Front Panel		Back Panel	
1	SD Card Scket and USB Port	1	Cooling Fan
2	IR Received Window	2	AC Input & Fuse
3	Screen	3	Zone 1-6 100V Output
4	MP3 Control Key	4	4-16 Ohm/70V/100V Output
5	Zone 1-6 Volume Control	5	Mute Switch
6	Output Signal Level Indicator	6	Line Output
7	Mic 1/2, Line3,1,2,MP3 volume control	7	Line 1,2 input
8	Mic Echo and time control	8	Mic Phantom & Mic2/Line3 Switch
9	Bass and Treble Equalizer Adjustment	9	Mic2/Line 3 XLR Input
10	Master Volume control	10	6.35mm Mic 1 input
11	Power Switch	11	FM antenna

Whats in the Box :-

- 1 x Amplifier
- 1 x Quick Start Guide
- 1 x Remote
- 1 x Rack Mount Clamp
- 1 x FM Antenna